


SANWA CD771

DIGITAL MULTITESTER



SPECIFICATION



| CD771 | Measuring range | Best accuracy | Resolution | Input impedance |
|---------------|--|---------------|------------|-----------------------|
| DCV | 400m/4/40/400/1000V | ± (0.5%+2) | 0.1mV | DCV: 10M~ 100MΩ |
| ACV | 4/40/400/1000V | ± (1.2%+7) | 1mV | ACV: 10M~ 11MΩ |
| DCA | 400μ/4000μ/40m/400m/4/10A | ± (1.4%+3) | 0.1μ | |
| ACA | 400μ/4000μ/40m/400m/4/10A | ± (1.8%+5) | 0.1μ | |
| Resistance | 400/4k/40k/400k/4M/40MΩ | ± (1.2%+5) | 0.1Ω | |
| Capacitance | 50n/500n/5μ/50μ/100μF | ± (5%+10) | 0.01nF | |
| Frequency | 5/50/500/5k/50k/100kHz | ± (0.3%+3) | 0.001Hz | |
| Continuity | Buzzer sounds and LED lights up at between 0Ω and 85Ω (±45Ω). Open voltage: approx. 0.4V | | | |
| Diode test | Open voltage: approx. 1.5V | | | |
| Battery check | Approximate value (30Ω load) 1.5V battery only | | | |

| | | |
|-------------------------------|---|-------|
| Bandwidth | 40~400Hz (sine wave) | |
| Fuse / Battery | 0.5A/1000V 30kA Φ6.35X32mm 10A/1000V 30kA Φ10X38mm | R6P×2 |
| Size / Mass | H166×W82×D44mm/360g | |
| Standard accessories included | Test lead (TL-23a), Instruction manual | |